

CRYPTOBOX 500 HD



- 1x DVB-S / DVB-S2 tuner
- 1x Card Reader
- 1x HDMI port
- 1x SCART
- 1x RS232
- 2x USB 2.0 (1x Front, 1x Rear panel)
- 1x LAN RJ 45
- 1x S/PDIF optical digital audio output
- Chipset: ALI3606
- Flash Memory: 8 MByte
- DDRII Memory: 128 Mbyte
- Signal Level -65 do -25 dBm
- LNB power and polarization
- Vertical: +13V/+14V,
- Horizontal: +18V/+19V
- Power max. 25W
- Frequency range 950 MHz do 2150 MHz
- Video resolution 1080i/p, 720p, 576i/p, 480i/p
- DiseqC 1.0/1.1/1.2/1.3 USALS 13V/18V, 0/22K
- 7-segment Display
- 7-day electronic guide
- Fast Scan
- Time Shift recording and PVR function
- PIG (Picture in Graphic)
- FTP manager, games, weather, stock market information, networking capability and many more...
- Automatic PAL / NTSC conversion
- 6000 TV / Radio Stations
- 8 the favorite groups
- Support FAT32 and NTFS
- media player formats:
- audio MP3, OGG, FLAC
- video AVI, MKV, TS, TP, TRP, MPG, MP4
- picture JPEG, BMP, GIF