

CRYPTOBOX 500 HD MINI



1x DVB-S / DVB-S2 tuner

1x Card Reader

1x HDMI port

1x RS232 via jack

1x USB 2.0

1x LAN RJ 45

1x S/PDIF

1x IR eye

Chipset: ALI3606

Flash Memory: 8 MByte

DDRII Memory: 128 Mbyte

Signal Level -65 do -25 dBm

LNB power and polarization

Vertical: +13V/+14V,

Horizontal: +18V/+19V

Power max. 25W

Frequency range 950 MHz do 2150 MHz

Video resolution 1080i/p, 720p, 576i/p, 480i/p

DiseqC 1.0/1.1/1.2/1.3 USALS 13V/18V, 0/22K

7-day electronic guide

Fast Scan

Time Shift recording and PVR function

PIG (Picture in Graphic)

FTP manager, games, weather, stock market information, networking capability and many more...

Automatic PAL / NTSC conversion

6000 TV / Radio Stations

8 the favorite groups

Support FAT32 and NTFS

media player formats:

audio MP3, OGG, FLAC

video AVI, MKV, TS, TP, TRP, MPG, MP4

picture JPEG, BMP, GIF

